



Predator WiFi

WiFi / 3G Video Intercom

GLOBAL

**NEW
For 2015**



- Speak to, and see your visitor from your smart-phone.
- Easy wireless connection to existing home wifi.
- Up to 150 metre range with directional antenna (dependant on location of router in house).
- Can call up to 4 devices at the same time.
- Get a video call from your gate / door even when away from home!
- No data use when phone on wifi connection.
- 2 year manufacturers warranty.

Predator WiFi

WiFi / 3G Video Intercom



Search Predator-WiFi

- Simple setup by mobile phone. Connect to the intercom directly through your phone's wifi, enter the pass code for the home hub wifi and the device is connected.
- View the gate/door and open any time with monitoring mode.
- Still works locally on wifi network even if broadband goes down.
- Can work with most market standard outdoor wifi repeaters for extended range.

Predator WiFi

WiFi / 3G Video Intercom



Technical Details

Power Supply	24vdc (adaptor included)	App name	Predator Wifi
Current Consumption	80mA standby, 300mA calling.	Audio	Half duplex loud speaker mode (Press mic icon to speak)
Relay Outputs	1	Keypad option	yes
Relay type	N/O & N/C contacts	Keypad relays	3
Relay time	Adjustable 1-10 secs	Keypad codes	1200
Relay load	2A 24v AC max	Wifi range	200m with directional antenna.
IP rating	IP55	Wifi standard	802.11b/g/n
Camera	Colour, 110 degree, 640x480 pixel	Security	6 digit passcode protected
Night vision	Yes, by infrared illumination	Uplink bandwidth	110K bits/sec